

## Eaton 9PX UPS technical specifications (5 and 6 kVA models\*)

| Model overv       | view                       |           |  |                              |                 |
|-------------------|----------------------------|-----------|--|------------------------------|-----------------|
| Catalog<br>number | Power rating<br>(VA/watts) | Input     | Output   | Dimensions<br>(HxWxD, in.)** | Weight<br>(lb.) |
| 208V output,      | 50/60 Hz bundles           | 5         |  |                              |                 |
| 9PX5K             | 5000/4500                  | L6-30P*** | (2) L6-30R, (2) L6-20R,<br>Hardwired             | 5.1 (3U) x 17.3 x 28.4       | 106             |
| 9PX6K             | 6000/5400                  | L6-30P*** | (2) L6-30R, (2) L6-20R,<br>Hardwired             | 5.1 (3U) x 17.3 x 28.4       | 106             |
| 120/208V out      | put, 50/60 Hz bun          | dles      |  |                              |                 |
| 9PX5KTF5          | 5000/4500                  | L6-30P*** | (1) L6-30R, (2) L6-20R,<br>(18) 5-20R, Hardwired | 10.2 (6U) x 17.3 x 28.4      | 201             |
| 9PX5KP1           | 5000/4500                  | L6-30P    | (1) L14-30R, (1) L6-30R,<br>(6) 5-20R            | 10.2 (6U) x 17.3 x 28.4      | 203             |
| 9PX5KP2           | 5000/4500                  | Hardwired | Hardwired  | 10.2 (6U) x 17.3 x 28.4      | 201             |
| 9PX6KTF5          | 6000/5400                  | L6-30P*** | (1) L6-30R, (2) L6-20R,<br>(18) 5-20R, Hardwired | 10.2 (6U) x 17.3 x 28.4      | 201             |
| 9PX6KP1           | 6000/5400                  | L6-30P    | (1) L14-30R, (1) L6-30R,<br>(6) 5-20R            | 10.2 (6U) x 17.3 x 28.4      | 203             |
| 9PX6KP2           | 6000/5400                  | Hardwired | Hardwired  | 10.2 (6U) x 17.3 x 28.4      | 201             |

\*\*Each module of every 9PX bundle ships with a 4-post rail kit. \*\*\*Terminal block with L6-30P cord.

## Battery backup times (in minutes)\*\*\*\*

|              | Internal  |        |         |         |         |
|--------------|-----------|--------|---------|---------|---------|
| Load (watts) | Batteries | +1 EBM | +2 EBMs | +3 EBMs | +4 EBMs |
| 5400         | 3.0       | 16     | 28      | 47      | 58      |
| 4050         | 4.5       | 24     | 45      | 62      | 90      |
| 2700         | 8.5       | 38     | 71      | 104     | 133     |
| 1350         | 22.0      | 85     | 147     | 214     | 287     |
| 540          | 57.0      | 203    | 399     | 554     | 755     |

\*\*\*\*Runtimes are shown at full load with maximum power factor, are approximate and may vary with equipment, configuration, battery age, temperature, etc. View interactive runtime graphs at <u>www.eaton.com/9PX</u>.

## **Additional specifications**

| General                                   |  |  |
|---|--|--|
| Topology                                  | Double-conversion online   |  |
| Configuration                             | Rack/tower   |  |
| Color                                     | Black and silver   |  |
| Diagnostics                               | Full system self test at power up  |  |
| Warranty                                  | 2 years  |  |
| Rail kit                                  | 4-post rail kit and tower pedestals included; Optional 2-post rail kit available, part number: RK2PC |  |
| Remote emergency power off (REPO)         | ROO and RPO: Rear deck emergency stop connectors (for remote on/off and power off)                   |  |
| Contents (Ships with the following items) | UPS<br>Network-MS Web/SNMP card  |  |
| iene in ignerie,                          | 4-post rail kit  |  |
|   | User manual  |  |
|   | Quick start guide  |  |
|   | Tower pedestals  |  |
|   | Intelligent Power Software Suite CD  |  |
|   | RS-232 serial cable  |  |

|                                     | USB cable   |  |
|-------------------------------------|---|--|
|                                     | Cable gland for hardwire conection  |  |
|                                     | Phillips head screw driver  |  |
| Electrical input                    |   |  |
| Input voltage range                 | Full load: 176-276V, Derating: 100-276V                                       |  |
| Nominal voltage                     | 200/208/220/230/240V  |  |
| Default voltage                     | 9PX5K and 9PX6K: 208V   |  |
| Frequency                           | 50/60 Hz  |  |
| Frequency range                     | 60 Hz: 50–70 Hz, 50 Hz: 40–60 Hz  |  |
| Input power factor                  | >.99  |  |
| Input current distortion            | <5%   |  |
| Circuit breaker                     | (2) 20A for L6-20R  |  |
| Electrical output                   |   |  |
| Power ratings NEMA 5 kVA            | 200/208/220/230/240V: 5000 VA/4500 watts                                      |  |
| Power ratings NEMA 6 kVA            | 230/240V: 5400 watts  |  |
|                                     | 220V: 5100 watts  |  |
|                                     | 208V: 4800 watts  |  |
|                                     | 200V: 4600 watts  |  |
| Power ratings IEC 6 kVA             | 200/208/220/230/240V: 6000 VA/5400 watts                                      |  |
| Nominal voltage                     | 208V default (200/208/220/230/240V)   |  |
| Output voltage regulation           | ±1% steady-state  |  |
| Voltage THD                         | <2% for linear loads  |  |
| Power factor                        | 0.9   |  |
| Efficiency                          | 93% with resistive load   |  |
| Transfer time                       | 0 ms  |  |
| Battery                             |   |  |
| Optional extended battery           | 9PXEBM180RT   |  |
| module (EBM)                        |   |  |
| Maximum number of EBMs              | Add up to 4 EBMs  |  |
| Battery description                 | Sealed, lead-acid; maintenance free   |  |
| Battery management                  | ABM technology; 3-stage charging extends battery service life by 50% and      |  |
| Battery management                  | provides advance warning for battery replacement                              |  |
| Battery replacement                 | Hot-swappable internal batteries and EBMs                                     |  |
| Start on battery                    | Cold-start enabled; first cold start is always forbidden                      |  |
| Communications                      |   |  |
| User interface                      | Graphical display. UPS status in a single view.                               |  |
| LEDs                                | 4 status-indicating LEDs  |  |
| Communication ports                 | RS-232 (RJ45) ports; USB port as standard (HID). 6-foot RS-232 and USB cables |  |
| F                                   | included  |  |
| Communications card slot            | Network Card-MS included  |  |
| Power management software           | Eaton Intelligent Power Software Suite CD (included)                          |  |
| Environmental & standards           |   |  |
| RoHS compliance                     | Yes   |  |
| Surge protection                    | IEEE ANSI C62.41 Cat B2   |  |
| Heat dissipation (BTU/hr;           | 9PX5K: Online: 1150. Battery: 1560  |  |
| battery full charged, resistive     | 9PX6K: Online: 1245. Battery: 1895  |  |
| load)                               |   |  |
| Audible noise                       | <45 dB at 1 meter   |  |
| Operating temperature               | 0 to 40°C (32°F to 104°F)   |  |
| Safety conformance                  | CE / cULus / NOM  |  |
| EMC markings                        | IEC 62040-2:2006 Cat C2 / CISPR22 Class A / FCC part 15 Class A               |  |
| Storage temperature                 | 0 to 35°C (32°F to 95°F); without batteries: -15 to 60°C (5°F to 140°F)       |  |
| Relative humidity                   | 0 to 95% non-condensing   |  |
| Altitude                            | <1,000 meters for nominal power; 10% power derating every 1000 meters (up to  |  |
| ,                                   | 3000 meters) at 40°C  |  |
| *Due to continuing product improves | nent programs, specifications are subject to change without notice.           |  |

\*Due to continuing product improvement programs, specifications are subject to change without notice.